

Rack Safety Plus, 3 U, 208 / 240 V AC

Power Utilities

FEATURES

19", 3 U Power Distribution Unit with Emergency Stop function

Supplies AC mains power to electrical or electronic devices as a central power switch

208 V phase to phase or phase to neutral or 240 V phase to phase mains input

AC outputs with different connector types, switched by ON/OFF switch

Permanent AC Outputs (Service)

All outputs are protected by circuit breakers

The emergency stop function meets the requirements of EN 60947-5-1 and EN 60204-1 and is vandalism-proof

An additional external emergency stop push button can be connected to the system

SPECIFICATIONS

Table 1/3

Catalog Number	Product Type	Works With	Function	Input Voltage AC	Number of Phases	EMC Filter
21272-001	Power Distributor	Varistar, Varistar CP, Novastar	Emergency Stop	208 – 240 V	1	Yes
21272-003	Power Distributor	Varistar, Varistar CP, Novastar	Emergency Stop	208 – 240 V	1	No

Table 2/3

Catalog Number	Surge Arrester	Inrush Current Limiter	Residual Current Device	Circuit Breaker Cover	Rack Height	Socket Type
21272-001	Yes	No	No	No	3 U	IEC C13, IEC C19
21272-003	No	No	No	No	3 U	IEC C13 lockable

Table 3/3	
Catalog Number	Accessory Type
21272-001	Power distribution accessories
21272-003	Power distribution accessories

ADDITIONAL PRODUCT DETAILS

For exact configuration of optional features and example configuration please refer to the item(s) delivered table.

WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at www.nvent.com and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE