

Rack Safety Plus, 3 U, 120 V AC

Power Utilities

VLASTNOSTI

19", 3 U Power Distribution Unit with Emergency Stop function

Supplies AC mains power to electrical or electronic devices as a central power switch

120 V phase to neutral mains input

AC outputs with different connector types, switched by ON/OFF switch

Permanent AC Outputs (Service)

All outputs are protected by circuit breakers

The emergency stop function meets the requirements of EN 60947-5-1 and EN 60204-1 and is vandalism-proof

An additional external emergency stop push button can be connected to the system

SPECIFIKACE

Table 1/3

Katalogové číslo	Product Type	Works With	Function	Vstupní napětí AC	Počet fází	EMC Filter
21272-002	Power Distributor	Varistar, Varistar CP, Novastar	Emergency Stop	120 V min	1	Yes
21272-004	Power Distributor	Varistar, Varistar CP, Novastar	Emergency Stop	120 V min	1	No

Table 2/3

Katalogové číslo	Surge Arrester	Inrush Current Limiter	Residual Current Device	Circuit Breaker Cover	Rack Height	Typ zásuvky
21272-002	Yes	No	No	No	3 U	NEMA 5-15R, NEMA 5-20R
21272-004	No	No	No	No	3 U	NEMA 5-15R

Table 3/3

Katalogové číslo	Accessory Type
21272-002	Power distribution accessories
21272-004	Power distribution accessories

DALŠÍ PODROBNOSTI O PRODUKTU

For exact configuration of optional features and example configuration please refer to the item(s) delivered table.

UPOZORNĚNÍ

Produkty nVent musí být instalovány a používány pouze tak, jak je uvedeno v instrukčních listech a materiálech pro školení nVent. Instrukční listy jsou k dispozici na www.nvent.com a od vašeho zástupce zákaznického servisu nVent. Nesprávná instalace, zneužití, nesprávné použití nebo jiný nedostatek úplného dodržování pokynů a varování nVent může způsobit selhání produktu, poškození majetku, vážné zranění osob a smrt a/nebo zrušit vaši záruku.



Naše portfolio silných značek:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE