

# Rack Safety Plus, 3 U, 120 V AC

## Power Utilities

### FEATURES

19", 3 U Power Distribution Unit with Emergency Stop function

Supplies AC mains power to electrical or electronic devices as a central power switch

120 V phase to neutral mains input

AC outputs with different connector types, switched by ON/OFF switch

Permanent AC Outputs (Service)

All outputs are protected by circuit breakers

The emergency stop function meets the requirements of EN 60947-5-1 and EN 60204-1 and is vandalism-proof

An additional external emergency stop push button can be connected to the system

### SPECIFICATIONS

Table 1/3

| Catalog Number | Product Type      | Works With                      | Function       | Input Voltage AC | Number of Phases | EMC Filter |
|----------------|-------------------|---------------------------------|----------------|------------------|------------------|------------|
| 21272-002      | Power Distributor | Varistar, Varistar CP, Novastar | Emergency Stop | 120 V min        | 1                | Yes        |
| 21272-004      | Power Distributor | Varistar, Varistar CP, Novastar | Emergency Stop | 120 V min        | 1                | No         |

Table 2/3

| Catalog Number | Surge Arrester | Inrush Current Limiter | Residual Current Device | Circuit Breaker Cover | Rack Height | Socket Type            |
|----------------|----------------|------------------------|-------------------------|-----------------------|-------------|------------------------|
| 21272-002      | Yes            | No                     | No                      | No                    | 3 U         | NEMA 5-15R, NEMA 5-20R |
| 21272-004      | No             | No                     | No                      | No                    | 3 U         | NEMA 5-15R             |

| Table 3/3      |                                |
|----------------|--------------------------------|
| Catalog Number | Accessory Type                 |
| 21272-002      | Power distribution accessories |
| 21272-004      | Power distribution accessories |

ADDITIONAL PRODUCT DETAILS

For exact configuration of optional features and example configuration please refer to the item(s) delivered table.

WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at [www.nvent.com](http://www.nvent.com) and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.



Our powerful portfolio of brands:

CADDY   ERICO   HOFFMAN   ILSCO   SCHROFF   TRACHTE