

# Rack Safety Plus, 3 U, 208 / 240 V AC

## Servicios públicos de energía

### CARACTERÍSTICAS

19", 3 U Power Distribution Unit with Emergency Stop function

Supplies AC mains power to electrical or electronic devices as a central power switch

208 V phase to phase or phase to neutral or 240 V phase to phase mains input

AC outputs with different connector types, switched by ON/OFF switch

Permanent AC Outputs (Service)

All outputs are protected by circuit breakers

The emergency stop function meets the requirements of EN 60947-5-1 and EN 60204-1 and is vandalism-proof

An additional external emergency stop push button can be connected to the system

### ESPECIFICACIONES

Table 1/3

| Número de catálogo | Product Type      | Works With                      | Function       | Input Voltage AC | Number of Phases | EMC Filter |
|--------------------|-------------------|---------------------------------|----------------|------------------|------------------|------------|
| 21272-003          | Power Distributor | Varistar, Varistar CP, Novastar | Emergency Stop | 208 – 240 V      | 1                | No         |
| 21272-001          | Power Distributor | Varistar, Varistar CP, Novastar | Emergency Stop | 208 – 240 V      | 1                | Sí         |

Table 2/3

| Número de catálogo | Surge Arrester | Inrush Current Limiter | Residual Current Device | Circuit Breaker Cover | Rack Height | Socket Type      |
|--------------------|----------------|------------------------|-------------------------|-----------------------|-------------|------------------|
| 21272-003          | No             | No                     | No                      | No                    | 3 U         | IEC C13 lockable |
| 21272-001          | Sí             | No                     | No                      | No                    | 3 U         | IEC C13, IEC C19 |

Table 3/3

| Número de catálogo | Accessory Type                 |
|--------------------|--------------------------------|
| 21272-003          | Power distribution accessories |
| 21272-001          | Power distribution accessories |

## ADDITIONAL PRODUCT DETAILS

For exact configuration of optional features and example configuration please refer to the item(s) delivered table.

## ADVERTENCIA

Los productos nVent deben instalarse y usarse solo como se indica en las hojas de instrucciones y materiales de capacitación del producto nVent. Las hojas de instrucciones están disponibles en [www.nvent.com](http://www.nvent.com) y con su representante de atención al cliente de nVent. La instalación incorrecta, el mal uso, la aplicación incorrecta u otras fallas en el seguimiento completo de las instrucciones y advertencias de nVent pueden causar el mal funcionamiento del producto, daños a la propiedad, lesiones corporales graves y la muerte y/o anular la garantía.



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE