

Rack Safety Plus, 3 U, 120 V AC

Servicios públicos de energía

CARACTERÍSTICAS

19", 3 U Power Distribution Unit with Emergency Stop function

Supplies AC mains power to electrical or electronic devices as a central power switch

120 V phase to neutral mains input

AC outputs with different connector types, switched by ON/OFF switch

Permanent AC Outputs (Service)

All outputs are protected by circuit breakers

The emergency stop function meets the requirements of EN 60947-5-1 and EN 60204-1 and is vandalism-proof

An additional external emergency stop push button can be connected to the system

ESPECIFICACIONES

Table 1/3

Número de catálogo	Product Type	Works With	Function	Input Voltage AC	Number of Phases	EMC Filter
21272-002	Power Distributor	Varistar, Varistar CP, Novastar	Emergency Stop	120 V min	1	Sí
21272-004	Power Distributor	Varistar, Varistar CP, Novastar	Emergency Stop	120 V min	1	No

Table 2/3

Número de catálogo	Surge Arrester	Inrush Current Limiter	Residual Current Device	Circuit Breaker Cover	Rack Height	Socket Type
21272-002	Sí	No	No	No	3 U	NEMA 5-15R, NEMA 5-20R
21272-004	No	No	No	No	3 U	NEMA 5-15R

Table 3/3

Número de catálogo	Accessory Type
21272-002	Power distribution accessories
21272-004	Power distribution accessories

ADDITIONAL PRODUCT DETAILS

For exact configuration of optional features and example configuration please refer to the item(s) delivered table.

ADVERTENCIA

Los productos nVent deben instalarse y usarse solo como se indica en las hojas de instrucciones y materiales de capacitación del producto nVent. Las hojas de instrucciones están disponibles en www.nvent.com y con su representante de atención al cliente de nVent. La instalación incorrecta, el mal uso, la aplicación incorrecta u otras fallas en el seguimiento completo de las instrucciones y advertencias de nVent pueden causar el mal funcionamiento del producto, daños a la propiedad, lesiones corporales graves y la muerte y/o anular la garantía.



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE