

Rack Safety Plus, 3 U, 208 / 240 V AC

Energiföretag

FUNKTIONER

19", 3 U Power Distribution Unit with Emergency Stop function

Supplies AC mains power to electrical or electronic devices as a central power switch

208 V phase to phase or phase to neutral or 240 V phase to phase mains input

AC outputs with different connector types, switched by ON/OFF switch

Permanent AC Outputs (Service)

All outputs are protected by circuit breakers

The emergency stop function meets the requirements of EN 60947-5-1 and EN 60204-1 and is vandalism-proof

An additional external emergency stop push button can be connected to the system

SPECIFIKATIONER

Table 1/3

Katalognummer	Product Type	Fungerar med	Funktion	Input Voltage AC	Number of Phases	EMC Filter
21272-003	Power Distributor	Varistar, Varistar CP, Novastar	Emergency Stop	208 – 240 V	1	Nej
21272-001	Power Distributor	Varistar, Varistar CP, Novastar	Emergency Stop	208 – 240 V	1	Ja

Table 2/3

Katalognummer	Surge Arrester	Inrush Current Limiter	Residual Current Device	Circuit Breaker Cover	Rack Height	Socket Type
21272-003	Nej	Nej	Nej	Nej	3 U	IEC C13 lockable
21272-001	Ja	Nej	Nej	Nej	3 U	IEC C13, IEC C19

Table 3/3

Katalognummer	Tillbehörstyp
21272-003	Power distribution accessories
21272-001	Power distribution accessories

ADDITIONAL PRODUCT DETAILS

For exact configuration of optional features and example configuration please refer to the item(s) delivered table.

WARNING

nVent produkter ska installeras och användas endast så som anges i nVents bruksanvisning och utbildningsmaterial. Bruksanvisningar är tillgängliga på www.nvent.com och från din nVent kundtjänstrepresentant. Felaktig installation, missbruk, felapplicering eller annan brist i att helt följa nVents instruktioner och varningar kan orsaka att produkten brister, egendomsskador, allvarliga kroppsskador och dödsfall och/eller ogiltigförklara din garanti.



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE