

Socket Strip, UTE

Power Utilities



Modular, compact PDU with many function elements. Using a 1 U by 1 U aluminum chassis the PDU can easily be integrated in a rack with UTE outlets.

CERTIFICATIONS



FEATURES

230 V, 16 A

In accordance with NFC 61-303

Socket strip with UTE sockets

Mounting height 1 U

Horizontal and vertical mounting

Connecting cable 2 m, with SCHUKO/UTE plug

Socket strips can be rotated through all four directions (in 90° increments) during installation

SPECIFICATIONS

Table 1/2

Catalog Number	Socket Type	Voltage AC	Function	Color	Depth	Length
----------------	-------------	------------	----------	-------	-------	--------

60110-267	UTE	230 V	Transient Protection, Mains Suppression Filter	Grey	44 mm	438.5 mm
60110-227	UTE	230 V	Transient Protection	Grey	44 mm	438.5 mm
60110-226	UTE	230 V		Grey	44 mm	947.5 mm
60110-225	UTE	230 V		Grey	44 mm	438.5 mm
60110-224	UTE	230 V		Grey	44 mm	1753 mm
60110-223	UTE	230 V		Grey	44 mm	1202 mm
60110-222	UTE	230 V		Grey	44 mm	947.5 mm
60110-221	UTE	230 V		Grey	44 mm	438.5 mm
60110-229	UTE	230 V	Mains Suppression Filter	Grey	44 mm	438.5 mm
60110-220	UTE	230 V		Grey	44 mm	210 mm
60110-228	UTE	230 V	Overcurrent Protection	Grey	75 mm	438.5 mm
60110-230	UTE	230 V	Fault Current Protection	Grey	88 mm	438.5 mm
60110-231	UTE	230 V	Fault Current Protection, Overcurrent Protection	Grey	88 mm	438.5 mm

Table 2/2

Catalog Number	Product Type
60110-267	Socket Strip
60110-227	Socket Strip
60110-226	Socket Strip

Catalog Number	Product Type
60110-225	Socket Strip
60110-224	Socket Strip
60110-223	Socket Strip
60110-222	Socket Strip
60110-221	Socket Strip
60110-229	Socket Strip
60110-220	Socket Strip
60110-228	Socket Strip
60110-230	Socket Strip
60110-231	Socket Strip

ADDITIONAL PRODUCT DETAILS

Please order bracket for vertical mounting separately.

WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at www.nvent.com and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE