

## **TT-Flasher Flashing Light Alarm**



nVent RAYCHEM TraceTek TT-FLASHER-BE is a battery powered flashing light signal to indicate when a sensing cable or probe detects a leak.

## **FEATURES**

Simple to install and operate: a flashing RED light indicates that a leak has been detected

Intrinsically safe and rated for hazardous areas

A test button checks the battery voltage and integrity of the sensor wiring

## **SPECIFICATIONS**

Table 1/2								
Catalog Number	Item Name	IP Rating	NEMA Rating	Ambient Temperature	Battery Information	Projected Battery Life		
P000000837	TT-FLASHER- BE	IP66	4X	-20 to 40 °C	AA	2 Year - Nominal		

Table 2/2						
Catalog Number	Item Name	Weight				
P000000837	TT-FLASHER-BE	1.4 kg				

## **WARNING**

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at www.nvent.com and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.

**North America** 

Tel +1.800.545.6258 Fax +1.800.527.5703 thermal.info@nvent.com Europe, Middle East, Africa

Tel +32.16.213.511 Fax +32.16.213.604 thermal.info@nvent.com **Asia Pacific** 

Tel +86.21.2412.1688 Fax +86.21.5426.3167 cn.thermal.info@nvent.com **Latin America** 

Tel +1.713.868.4800 Fax +1.713.868.2333 thermal.info@nvent.com