

RackPower Intelligent Power Distribution Units

Data Solutions



RackPower Intelligent Power Distribution Units address controlling power on Cabinets as well as Open Frame Racks and Wall-Mount enclosures. Design your power solution using a variety of configuration options. The units are available in horizontal 19-in. rack or vertical mounting capabilities and a broad range of features.

If the portfolio of pre-configured items does not meet your needs, all PDUs can be configured to your specifications as a custom order. Contact Customer Service to place an order.

To configure a custom PDU, go to https://configurator.schroff.biz/PDU_Webapp/

INDUSTRY STANDARDS

Test to UL File E309439 UL 60950-1 Information Technology Equipment

Test to cUL File E309439 CSA-C22.2 No. 60950-1 Information Technology Equipment

Technology Equipment

FCC

CE

RoHS

REACH

FEATURES

Single or multi-phase

Input voltages North American 110 / 120 VAC or 208 VAC, European and Asia 230 VAC or 400 VAC

Global plug and receptacles NEMA and IEC rated

5 Configuration types: RP3000, RP2000, RP1500, RP1000, RP100

External communications and monitoring - protected and secure LAN connections

Local and remote power monitoring of single outlets and circuits showing data for current (AMP), voltage (Volt), power (kW), energy consumption (kWh) and power factor of entire PDU with a metering accuracy to within +/- 1%

Remote power on/off switch

Field replaceable, "hot-swappable", smart monitor (RP Meter) and DC module

19-in. Rack Mounting (1 and 2 RU offering)

Versatile vertical / rack and cabinet mounting

Surge protection

Dual power feed entry for single phase RackPower PDUs

Temperature Sensor or Temperature and Humidity Sensor

Power cord whip – various lengths, colors and plugs

Various cord length and plug styles available; also available in LSZH (low smoke zero halogen)

Mounting hardware included

SPECIFICATIONS

Color: Jet Black Material: Mild Steel Finish: Powder Coated Color Code: RAL 9005

| Table 1/2 | | | | | | |
|----------------------|----------------|--------|-------|-------|---------------------------|------------|
| Catalog Number | Article Number | Height | Width | Depth | Electrical Load Rating | Voltage AC |
| RPP110P30AP1 24 | 38736 | 1100mm | 80mm | 54mm | 30A | 110V |
| RPP208R20AP1 12 | 38743 | 438mm | 120mm | 45mm | 20A | 208V |
| RPP208P30AP1 24 | 38738 | 1100mm | 80mm | 54mm | 30A | 208V |
| RPP110R30AP1 10 | 38741 | 438mm | 120mm | 45mm | 30A | 110V |
| RP20P208P30A P124 | 38747 | 1350mm | 80mm | 54mm | 30A | 208V |
| RP10208P30AP 142 | 38755 | 1725mm | 80mm | 54mm | 30A | 208V |
| RPP208R20AP1 14 | 39328 | 478mm | 120mm | 45mm | 20A | 208V |
| RP30208P20AP 124 | 38762 | 1350mm | 80mm | 54mm | 20A | 208V |

| CatalogNumber | Article Number | Height | Width | Depth | Electrical Load Rating | Voltage AC |
|----------------------|----------------|--------|-------|-------|---------------------------|------------|
| RP10208P30AP 136B | 39336 | 1725mm | 80mm | 54mm | 30A | 208V |
| RP20110P30AP 124 | 38746 | 1350mm | 80mm | 54mm | 30A | 110V |
| RP10110P30AP 124 | 38754 | 1350mm | 80mm | 54mm | 30A | 110V |
| RP10208H30AP 112B | 39335 | 438mm | 120mm | 54mm | 30A | 208V |
| RPP110P20AP1 24 | 38735 | 1100mm | 80mm | 54mm | 20A | 110V |
| RPP110R20AP1 10 | 38742 | 438mm | 120mm | 45mm | 20A | 110V |
| RP20P208P20A P124 | 38748 | 1350mm | 80mm | 54mm | 20A | 208V |
| RPP208P20AP1 24 | 38737 | 1100mm | 80mm | 54mm | 20A | 208V |
| RP15208P30AP 124 | 38757 | 1350mm | 80mm | 54mm | 30A | 208V |
| RP10110P20AP 124 | 38753 | 1350mm | 80mm | 54mm | 20A | 110V |
| RP20110P20AP 124 | 38745 | 1350mm | 80mm | 54mm | 20A | 110V |
| RPP208R30AP1 10 | 38744 | 438mm | 120mm | 45mm | 30A | 208V |
| RP30208P20AP 324 | 38763 | 1700mm | 80mm | 54mm | 20A | 208V |

| CatalogNumber | Article Number | Height | Width | Depth | Electrical Load Rating | Voltage AC |
|----------------------|----------------|--------|-------|-------|---------------------------|------------|
| RP20P208P30A P324 | 38752 | 1700mm | 80mm | 54mm | 30A | 208V |
| RP20P208P20A P324 | 38751 | 1750mm | 80mm | 54mm | 20A | 208V |
| RP15208P30AP 324 | 38758 | 1700mm | 80mm | 54mm | 30A | 208V |
| RP10208P30AP 342B | 39277 | 1725mm | 80mm | 54mm | 30A | 208V |
| RP10208P30AP 327B | 39334 | 1700mm | 80mm | 54mm | 30A | 208V |
| RP30208P30AP 324 | 38761 | 1700mm | 80mm | 54mm | 30A | 208V |
| RP10208P60AP 318B | 39331 | 1700mm | 90mm | 60mm | 60A | 208V |
| RP10208P60AP 342B | 39333 | 1800mm | 90mm | 85mm | 60A | 208V |
| RP10208P50AP 342 | 38756 | 1800mm | 90mm | 85mm | 50A | 208V |

| Table 2/2 | | | | | | | |
|--------------------|----------------|------------------|--------------------|----------------------|-------------|------------|--|
| Catalog Number | Article Number | Number of Phases | Socket Quantity | Socket Type | Plug Type | Mounting | |
| RPP110P30AP1 24 | 38736 | 1Ph | 24 | NEMA 5-20R | NEMA L5-30P | Vertical | |
| RPP208R20AP1 12 | 38743 | 1Ph | 12 | C13 | NEMA L6-20P | Horizontal | |
| RPP208P30AP1 24 | 38738 | 1Ph | 24 | (20) C13, (4) C19 | NEMA L6-30P | Vertical | |

| CatalogNumber | Article Number | Number of Phases | SocketQuantity | Socket Type | Plug Type | Mounting |
|----------------------|----------------|------------------|----------------|----------------------|-------------|------------|
| RPP110R30AP1 10 | 38741 | 1Ph | 10 | NEMA 5-20R | NEMA L5-30P | Horizontal |
| RP20P208P30A P124 | 38747 | 1Ph | 24 | (21) C13, (3) C19 | NEMA L6-20P | Vertical |
| RP10208P30AP 142 | 38755 | 1Ph | 42 | (36) C13, (6) C19 | NEMA L6-30P | Vertical |
| RPP208R20AP1 14 | 39328 | 1Ph | 14 | (12) C13, (2) C19 | NEMA L6-20P | Horizontal |
| RP30208P20AP 124 | 38762 | 1Ph | 24 | (21) C13, (3) C19 | NEMA L6-20P | Vertical |
| RP10208P30AP 136B | 39336 | 1Ph | 36 | (30) C13, (6) C19 | NEMA L6-30P | Vertical |
| RP20110P30AP 124 | 38746 | 1Ph | 24 | NEMA 5-20R | NEMA L5-30P | Vertical |
| RP10110P30AP 124 | 38754 | 1Ph | 24 | NEMA 5-20R | NEMA L5-30P | Vertical |
| RP10208H30AP 112B | 39335 | 1Ph | 12 | (12) C13 | NEMA L6-30P | Vertical |
| RPP110P20AP1 24 | 38735 | 1Ph | 24 | NEMA 5-20R | NEMA L5-20P | Vertical |
| RPP110R20AP1 10 | 38742 | 1Ph | 10 | NEMA 5-20R | NEMA L5-20P | Horizontal |
| RP20P208P20A P124 | 38748 | 1Ph | 24 | (21) C13, (3) C19 | NEMA L6-30P | Vertical |
| RPP208P20AP1 24 | 38737 | 1Ph | 24 | (20) C13, (4) C19 | NEMA L6-20P | Vertical |

| CatalogNumber | Article Number | Number of Phases | SocketQuantity | Socket Type | Plug Type | Mounting |
|----------------------|----------------|------------------|----------------|----------------------|----------------------------------------|------------|
| RP15208P30AP 124 | 38757 | 1Ph | 24 | (21) C13, (3) C19 | NEMA L6-30P | Vertical |
| RP10110P20AP 124 | 38753 | 1Ph | 24 | NEMA 5-20R | NEMA L5-20P | Vertical |
| RP20110P20AP 124 | 38745 | 1Ph | 24 | NEMA 5-20R | NEMA L5-20P | Vertical |
| RPP208R30AP1 10 | 38744 | 1Ph | 10 | C13 | NEMA L6-30P | Horizontal |
| RP30208P20AP 324 | 38763 | 3Ph | 24 | (21) C13, (3) C19 | NEMA L6-20P | Vertical |
| RP20P208P30A P324 | 38752 | 3Ph | 24 | (21) C13, (3) C19 | NEMA L21-30P | Vertical |
| RP20P208P20A P324 | 38751 | 3Ph | 24 | (21) C13, (3) C19 | NEMA L21-20P | Vertical |
| RP15208P30AP 324 | 38758 | 3Ph | 24 | (21) C13, (3) C19 | NEMA L21-30P | Vertical |
| RP10208P30AP 342B | 39277 | 3Ph | 42 | (36) C13, (6) C19 | NEMA L21-30P | Vertical |
| RP10208P30AP 327B | 39334 | 3Ph | 27 | (21) C13, (6) C19 | NEMA L21-30P | Vertical |
| RP30208P30AP 324 | 38761 | 3Ph | 24 | (21) C13, (3) C19 | NEMA L21-30P | Vertical |
| RP10208P60AP 318B | 39331 | 3Ph | 18 | (6) C13, (12) C19 | IEC 60309 60A, 3P+E 9h Blue Plug | Vertical |
| RP10208P60AP 342B | 39333 | 3Ph | 42 | (6) C13, (12) C19 | IEC 60309 60A, 3P+E 9h Blue Plug | Vertical |

| CatalogNumber | Article Number | Number of Phases | SocketQuantity | Socket Type | Plug Type | Mounting |
|---------------------|----------------|------------------|----------------|----------------------|-----------|----------|
| RP10208P50AP 342 | 38756 | 3Ph | 42 | (36) C13, (6) C19 | CS8365C | Vertical |

WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at www.nvent.com and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE