

# nVent ERIFLEX FleXbus Transformer Cover **IP2X for 1 Conductor per Phase**

# **Data Solutions**



#### **CERTIFICATIONS**









#### **FEATURES**

Input/output for neutral/ground conductor

Resistance to solvent and hydrocarbon splashes

Installs quickly and easily


UV resistance


## **SPECIFICATIONS**

Table 1/2							
Catalog Number	Article Number	Material	Working Temperature	Length (L)	Width (W)	Depth (D)	
FLEXCOVIP2XO NE	508160	Polyvinylchlorid e	-40 to 140°C	465mm	182mm	126mm	

Table 2/2					
Catalog Number	Article Number	Unit Weight			
FLEXCOVIP2XONE	508160	0.53kg			

# **DIAGRAMS**





## **WARNING**

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at www.nvent.com and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE