

# TT-Flasher Flashing Light Alarm



nVent RAYCHEM TraceTek TT-FLASHER-BE is a battery powered flashing light signal to indicate when a sensing cable or probe detects a leak.

## FEATURES

Simple to install and operate: a flashing RED light indicates that a leak has been detected

Intrinsically safe and rated for hazardous areas

A test button checks the battery voltage and integrity of the sensor wiring

## SPECIFICATIONS

Table 1/2

Catalog Number	Item Name	IP Rating	NEMA Rating	Ambient Temperature	Battery Information	Projected Battery Life
P000000837	TT-FLASHER-BE	IP66	4X	-20 to 40 °C	AA	2 Year - Nominal

Table 2/2

Catalog Number	Item Name	Weight
P000000837	TT-FLASHER-BE	1.4 kg

## WARNING

nVent products shall be installed and used only as indicated in nVent's product instruction sheets and training materials. Instruction sheets are available at [www.nvent.com](http://www.nvent.com) and from your nVent customer service representative. Improper installation, misuse, misapplication or other failure to completely follow nVent's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.

**North America**

Tel +1.800.545.6258

Fax +1.800.527.5703

[thermal.info@nvent.com](mailto:thermal.info@nvent.com)

**Europe, Middle East,  
Africa**

Tel +32.16.213.511

Fax +32.16.213.604

[thermal.info@nvent.com](mailto:thermal.info@nvent.com)

**Asia Pacific**

Tel +86.21.2412.1688

Fax +86.21.5426.3167

[cn.thermal.info@nvent.com](mailto:cn.thermal.info@nvent.com)

**Latin America**

Tel +1.713.868.4800

Fax +1.713.868.2333

[thermal.info@nvent.com](mailto:thermal.info@nvent.com)

Our powerful portfolio of brands:

**RAYCHEM   PYROTENAX   TRACER   NUHEAT**