

# Socket Strip, SCHUKO

## Servicios públicos de energía



Modular, compact PDU with many function elements. Using a 1U by 1U aluminum chassis the PDU can easily be integrated in a rack with Schuko outlets.

### CERTIFICACIONES



### CARACTERÍSTICAS

230 V, 16 A

Horizontal or vertical mounting

Connecting cable 2 m with SCHUKO/UTE plug

In accordance with DIN 57620, VDE 0620

Installation height 1 U

Socket strips with SCHUKO sockets

Socket strips can be rotated through all four directions (in 90° increments) during installation

### ESPECIFICACIONES

Table 1/2

| Número de catálogo | Socket Type | Voltage AC | Function | Color | Profundidad | Longitud |
|--------------------|-------------|------------|----------|-------|-------------|----------|
| 60110-200          | SCHUKO      | 230 V      |          | Gris  | 44 mm       | 184 mm   |

| Número de catálogo | Socket Type | Voltage AC | Function                                         | Color | Profundidad | Longitud |
|--------------------|-------------|------------|--------------------------------------------------|-------|-------------|----------|
| 60110-201          | SCHUKO      | 230 V      |                                                  | Gris  | 44 mm       | 210 mm   |
| 60110-202          | SCHUKO      | 230 V      |                                                  | Gris  | 44 mm       | 438.5 mm |
| 60110-203          | SCHUKO      | 230 V      |                                                  | Gris  | 44 mm       | 947.5 mm |
| 60110-204          | SCHUKO      | 230 V      |                                                  | Gris  | 44 mm       | 1202 mm  |
| 60110-205          | SCHUKO      | 230 V      |                                                  | Gris  | 44 mm       | 1753 mm  |
| 60110-206          | SCHUKO      | 230 V      |                                                  | Gris  | 44 mm       | 438.5 mm |
| 60110-207          | SCHUKO      | 230 V      |                                                  | Gris  | 44 mm       | 947.5 mm |
| 60110-208          | SCHUKO      | 230 V      |                                                  | Gris  | 44 mm       | 1202 mm  |
| 60110-209          | SCHUKO      | 230 V      |                                                  | Gris  | 44 mm       | 1753 mm  |
| 60110-210          | SCHUKO      | 230 V      | Transient Protection                             | Gris  | 44 mm       | 438.5 mm |
| 60110-211          | SCHUKO      | 230 V      | Transient Protection                             | Gris  | 44 mm       | 947.5 mm |
| 60110-214          | SCHUKO      | 230 V      | Mains Suppression Filter                         | Gris  | 44 mm       | 438.5 mm |
| 60110-266          | SCHUKO      | 230 V      | Transient Protection, Mains Suppression Filter   | Gris  | 44 mm       | 438.5 mm |
| 60110-212          | SCHUKO      | 230 V      | Overcurrent Protection                           | Gris  | 75 mm       | 438.5 mm |
| 60110-216          | SCHUKO      | 230 V      | Fault Current Protection                         | Gris  | 88 mm       | 438.5 mm |
| 60110-217          | SCHUKO      | 230 V      | Fault Current Protection, Overcurrent Protection | Gris  | 88 mm       | 438.5 mm |

Table 2/2

| Número de catálogo | Product Type |
|--------------------|--------------|
| 60110-200          | Socket Strip |
| 60110-201          | Socket Strip |
| 60110-202          | Socket Strip |
| 60110-203          | Socket Strip |
| 60110-204          | Socket Strip |
| 60110-205          | Socket Strip |
| 60110-206          | Socket Strip |
| 60110-207          | Socket Strip |
| 60110-208          | Socket Strip |
| 60110-209          | Socket Strip |
| 60110-210          | Socket Strip |
| 60110-211          | Socket Strip |
| 60110-214          | Socket Strip |
| 60110-266          | Socket Strip |
| 60110-212          | Socket Strip |
| 60110-216          | Socket Strip |
| 60110-217          | Socket Strip |

## ADDITIONAL PRODUCT DETAILS

---

Please order mounting bracket for vertical mounting separately.

## ADVERTENCIA

---

Los productos nVent deben instalarse y usarse solo como se indica en las hojas de instrucciones y materiales de capacitación del producto nVent. Las hojas de instrucciones están disponibles en [www.nvent.com](http://www.nvent.com) y con su representante de atención al cliente de nVent. La instalación incorrecta, el mal uso, la aplicación incorrecta u otras fallas en el seguimiento completo de las instrucciones y advertencias de nVent pueden causar el mal funcionamiento del producto, daños a la propiedad, lesiones corporales graves y la muerte y/o anular la garantía.



Our powerful portfolio of brands:

**CADDY   ERICO   HOFFMAN   ILSCO   SCHROFF   TRACHTE**