

# RackPower PDU, RP2xxx, 100-240 VAC, 1-phase

## Servizi di distribuzione di energia

Modular, compact intelligent PDU with inlet metering and remote outlet switching. Ultra-Low Profile Design with only 50 mm height.

### CARATTERISTICHE

RackPower RP2xxx Intelligent Power Distribution Units monitors input power of the entire PDU and offers remote switching of individual outlets, provides billing grade unit level monitoring

High Visibility Data Display and Interactive Graphic Display

Measure circuit breaker loads across redundant feeds to avoid accidental downtime

Enables smart load balancing for power efficiency and maximized capacity utilization

Gigabit Ethernet Interface and redundant Ethernet (10/100)

iPDU DC power redundancy solution for up to 64 PDU's

Toolless Hot-Swap Controller

Input Voltage Range 100 - 240 VAC, 1-phase L-N or L-L

Input connector C20

C13, C19 outlets

User-defined power-on time delay or automatic power-on sequencing

### SPECIFICHE

Table 1/2

| Numero catalogo | Product Type | Socket Type      | Colore | Lunghezza | Voltage AC | Function                          |
|-----------------|--------------|------------------|--------|-----------|------------|-----------------------------------|
| RP2326          | Socket Strip | IEC C13, IEC C19 | Nero   | 1490 mm   | 230 V      | Input Monitored, Switched Outlets |

Table 2/2

| Numero catalogo | Profondità | Larghezza |
|-----------------|------------|-----------|
|-----------------|------------|-----------|

|        |       |       |
|--------|-------|-------|
| RP2326 | 53 mm | 52 mm |
|--------|-------|-------|

## ADDITIONAL PRODUCT DETAILS

Please order bracket for vertical mounting separately.

## AVVERTENZA

AVVERTENZA: i prodotti nVent devono essere installati e usati solo secondo le indicazioni riportate nei fogli delle istruzioni del prodotto nVent e nei materiali di formazione. I fogli di istruzioni sono disponibili sul sito [www.nvent.com](http://www.nvent.com) e presso il vostro rappresentante locale dell'assistenza clienti di nVent. Un'installazione scorretta, l'uso improprio, l'applicazione errata o altre inosservanze delle istruzioni e delle avvertenze di nVent possono causare un malfunzionamento del prodotto, danni alle proprietà, lesioni corporee gravi e morte e/o l'annullamento della garanzia.



Our powerful portfolio of brands:

**CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE**