


Socket Strip, UTE

Instalacje zasilające



Modular, compact PDU with many function elements. Using a 1 U by 1 U aluminum chassis the PDU can easily be integrated in a rack with UTE outlets.

CERTYFIKATY



FUNKCJE

230 V, 16 A

In accordance with NFC 61-303

Socket strip with UTE sockets

Mounting height 1 U

Horizontal and vertical mounting

Connecting cable 2 m, with SCHUKO/UTE plug

Socket strips can be rotated through all four directions (in 90° increments) during installation

OKREŚLENIU SPECYFIKACJI

Table 1/2

Numer katalogowy	Socket Type	Voltage AC	Function	Kolor	Głębokość	Długość
60110-220	UTE	230 V		Szara	44 mm	210 mm

Numer katalogowy	Socket Type	Voltage AC	Function	Kolor	Głębokość	Długość
60110-221	UTE	230 V		Szara	44 mm	438.5 mm
60110-222	UTE	230 V		Szara	44 mm	947.5 mm
60110-223	UTE	230 V		Szara	44 mm	1202 mm
60110-224	UTE	230 V		Szara	44 mm	1753 mm
60110-225	UTE	230 V		Szara	44 mm	438.5 mm
60110-226	UTE	230 V		Szara	44 mm	947.5 mm
60110-227	UTE	230 V	Transient Protection	Szara	44 mm	438.5 mm
60110-229	UTE	230 V	Mains Suppression Filter	Szara	44 mm	438.5 mm
60110-267	UTE	230 V	Transient Protection, Mains Suppression Filter	Szara	44 mm	438.5 mm
60110-228	UTE	230 V	Overcurrent Protection	Szara	75 mm	438.5 mm
60110-230	UTE	230 V	Fault Current Protection	Szara	88 mm	438.5 mm
60110-231	UTE	230 V	Fault Current Protection, Overcurrent Protection	Szara	88 mm	438.5 mm

Table 2/2

Numer katalogowy	Product Type
60110-220	Socket Strip
60110-221	Socket Strip
60110-222	Socket Strip

Numer katalogowy	Product Type
60110-223	Socket Strip
60110-224	Socket Strip
60110-225	Socket Strip
60110-226	Socket Strip
60110-227	Socket Strip
60110-229	Socket Strip
60110-267	Socket Strip
60110-228	Socket Strip
60110-230	Socket Strip
60110-231	Socket Strip

ADDITIONAL PRODUCT DETAILS

Please order bracket for vertical mounting separately.

OSTRZEŻENIE

Produkty nVent powinny być instalowane i używane wyłącznie zgodnie z instrukcjami i materiałami szkoleniowymi nVent. Instrukcje są dostępne na stronie www.nvent.com oraz u przedstawiciela działu obsługi klienta firmy nVent. Nieprawidłowa instalacja, niewłaściwe użycie, niewłaściwe zastosowanie lub inne nieprzestrzeganie instrukcji i ostrzeżeń nVent może spowodować nieprawidłowe działanie produktu, uszkodzenie mienia, poważne obrażenia ciała i śmierć i/lub utratę gwarancji.



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE