

Socket Strip, UTE

Concessionárias de energia



Modular, compact PDU with many function elements. Using a 1 U by 1 U aluminum chassis the PDU can easily be integrated in a rack with UTE outlets.

CERTIFICAÇÕES



RECURSOS

230 V, 16 A

In accordance with NFC 61-303

Socket strip with UTE sockets

Mounting height 1 U

Horizontal and vertical mounting

Connecting cable 2 m, with SCHUKO/UTE plug

Socket strips can be rotated through all four directions (in 90° increments) during installation

ESPECIFICAÇÕES

Table 1/2

Número do catálogo	Socket Type	Voltage AC	Function	Cor	Profundidade	Comprimento
60110-220	UTE	230 V		Grey	44 mm	210 mm

Número do catálogo	Socket Type	Voltage AC	Function	Cor	Profundidade	Comprimento
60110-221	UTE	230 V		Grey	44 mm	438.5 mm
60110-222	UTE	230 V		Grey	44 mm	947.5 mm
60110-223	UTE	230 V		Grey	44 mm	1202 mm
60110-224	UTE	230 V		Grey	44 mm	1753 mm
60110-225	UTE	230 V		Grey	44 mm	438.5 mm
60110-226	UTE	230 V		Grey	44 mm	947.5 mm
60110-227	UTE	230 V	Transient Protection	Grey	44 mm	438.5 mm
60110-229	UTE	230 V	Mains Suppression Filter	Grey	44 mm	438.5 mm
60110-267	UTE	230 V	Transient Protection, Mains Suppression Filter	Grey	44 mm	438.5 mm
60110-228	UTE	230 V	Overcurrent Protection	Grey	75 mm	438.5 mm
60110-230	UTE	230 V	Fault Current Protection	Grey	88 mm	438.5 mm
60110-231	UTE	230 V	Fault Current Protection, Overcurrent Protection	Grey	88 mm	438.5 mm

Table 2/2

Número do catálogo	Product Type
60110-220	Socket Strip
60110-221	Socket Strip
60110-222	Socket Strip

Número do catálogo	Product Type
60110-223	Socket Strip
60110-224	Socket Strip
60110-225	Socket Strip
60110-226	Socket Strip
60110-227	Socket Strip
60110-229	Socket Strip
60110-267	Socket Strip
60110-228	Socket Strip
60110-230	Socket Strip
60110-231	Socket Strip

ADDITIONAL PRODUCT DETAILS

Please order bracket for vertical mounting separately.

AVISO

Os produtos nVent devem ser instalados e utilizados apenas conforme indicado nas fichas de instrução do produto e materiais de treinamento da nVent. As fichas de instrução estão disponíveis em www.nVent.com e com nossos representantes de atendimento ao cliente nVent. A instalação inadequada, uso incorreto, aplicação incorreta ou outra falha qualquer em seguir completamente as instruções e avisos da nVent podem levar ao mau funcionamento do produto, danos à propriedade, lesões corporais graves e morte, e/ou anular sua garantia.



Our powerful portfolio of brands:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE