

# Socket Strip, UTE

# **Data Solutions**



Modular, compact PDU with many function elements. Using a 1 U by 1 U aluminum chassis the PDU can easily be integrated in a rack with UTE outlets.

#### **CERTIFICATIONS**





#### **CARACTERISTICI**

230 V, 16 A

In accordance with NFC 61-303

Socket strip with UTE sockets

Mounting height 1 U

Horizontal or vertical mounting

Connecting cable 2 m, with SCHUKO/UTE plug

Socket strips can be rotated through all four directions (in 90° increments) during installation

# SPECIFICAȚII

Material: Aluminiu; Polyamide

**Color:** Grey

**Product Type:** Socket Strip

Table 1/2							
Număr de catalog	Socket Type	Socket Quantity	Switched Outlets	Voltage AC	Function	Package Quantity	
60110-220	UTE	4	No	230V		1	
60110-221	UTE	9	No	230V		1	
60110-222	UTE	12	No	230V		1	
60110-223	UTE	15	No	230V		1	
60110-224	UTE	19	No	230V		1	
60110-225	UTE	8	Yes	230V		1	
60110-226	UTE	12	Yes	230V		1	
60110-227	UTE	8	No	230V	Transient Protection	1	
60110-228	UTE	6	No	230V	Overcurrent Protection	1	
60110-229	UTE	7	No	230V	Mains Suppression Filter	1	
60110-230	UTE	6	No	230V	Fault Current Protection	1	
60110-231	UTE	6	No	230V	Fault Current Protection, Overcurrent Protection	1	
60110-267	UTE	6	No	230V	Transient Protection, Mains Suppression Filter	1	

Table 2/2							
Număr de catalog	Depth	Finish	Length				
60110-220	44mm	Anodized	210mm				
60110-221	44mm	Anodized	438.5mm				

Număr de catalog	Depth	Finish	Length
60110-222	44mm	Anodized	947.5mm
60110-223	44mm	Anodized	1202mm
60110-224	44mm	Anodized	1753mm
60110-225	44mm	Anodized	438.5mm
60110-226	44mm	Anodized	947.5mm
60110-227	44mm	Anodized	438.5mm
60110-228	75mm	Anodized	438.5mm
60110-229	44mm	Anodized	438.5mm
60110-230	88mm	Anodized	438.5mm
60110-231	88mm	Anodized	438.5mm
60110-267	44mm	Anodized	438.5mm

# **DETALII SUPLIMENTARE DESPRE PRODUS**

Please order bracket for vertical mounting separately.

### **AVERTIZARE**

Produsele nVent trebuie instalate și utilizate numai așa cum este indicat în fișele de instrucțiuni și materialele de formare ale nVent. Fișele de instrucțiuni sunt disponibile pe www.nvent.com și de la reprezentantul dvs. de servicii clienți nVent. O instalare incorectă, o utilizare abuzivă, o aplicare greșită sau orice altă lipsă de respectare completă a instrucțiunilor și avertismentelor nVent poate duce la defectarea produsului, la deteriorarea proprietății, la răniri corporale grave și moarte și/sau poate anula garanția dvs.



Portofoliul nostru puternic de mărci:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE